

01/26/99

jc551 U.S. PTO
09/237356
01/26/99

Box PATENT APPLICATION
Assistant Commissioner for Patents
Washington, D.C. 20231

Enclosed for filing is the utility patent application of Sandeep Chennakeshu, Kambiz Zangi and Gregory E. Bottomley for REDUCED COMPLEXITY MLSE EQUALIZER FOR M-ARY MODULATED SIGNALS.

COLE
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210
2211
2212
2213
2214
2215
2216
2217
2218
2219
2220
2221
2222
2223
2224
2225
2226
2227
2228
2229
2230
2231
2232
2233
2234
2235
2236
2237
2238
2239
2240
2241
2242
2243
2244
2245
2246
2247
2248
2249
2250
2251
2252
2253
2254
2255
2256
2257
2258
2259
2260
2261
2262
2263
2264
2265
2266
2267
2268
2269
2270
2271
2272
2273
2274
2275
2276
2277
2278
2279
2280
2281
2282
2283
2284
2285
2286
2287
2288
2289
2290
2291
2292
2293
2294
2295
2296
2297
2298
2299
2300
2301
2302
2303
2304
2305
2306
2307
2308
2309
2310
2311
2312
2313
2314
2315
2316
2317
2318
2319
2320
2321
2322
2323
2324
2325
2326
2327
2328
2329
2330
2331
2332
2333
2334
2335
2336
2337
2338
2339
2340
2341
2342
2343
2344
2345
2346
2347
2348
2349
2350
2351
2352
2353
2354
2355
2356
2357
2358
2359
2360
2361
2362
2363
2364
2365
2366
2367
2368
2369
2370
2371
2372
2373
2374
2375
2376
2377
2378
2379
2380
2381
2382
2383
2384
2385
2386
2387
2388
2389
2390
2391
2392
2393
2394
2395
2396
2397
2398
2399
2400
2401
2402
2403
2404
2405
2406
2407
2408
2409
2410
2411
2412
2413
2414
2415
2416
2417
2418
2419
2420
2421
2422
2423
2424
2425
2426
2427
2428
2429
2430
2431
2432
2433
2434
2435
2436
2437
2438
2439
2440
2441
2442
2443
2444
2445
2446
2447
2448
2449
2450
2451
2452
2453
2454
2455
2456
2457
2458
2459
2460
2461
2462
2463
2464
2465
2466
2467
2468
2469
2470
2471
2472
2473
2474
2475
2476
2477
2478
2479
2480
2481
2482
2483
2484
2485
2486
2487
2488
2489
2490
2491
2492
2493
2494
2495
2496
2497
2498
2499
2500
2501
2502
2503
2504
2505
2506
2507
2508
2509
2510
2511
2512
2513
2514
2515
2516
2517
2518
2519
2520
2521
2522
2523
2524
2525
2526
2527
2528
2529
2530
2531
2532
2533
2534
2535
2536
2537
2538
2539
2540
2541
2542
2543
2544
2545
2546
2547
2548
2549
2550
2551
2552
2553
2554
2555
2556
2557
2558
2559
2560
2561
2562
2563
2564
2565
2566
2567
2568
2569
2570
2571
2572
2573
2574
2575
2576
2577
2578
2579
2580

- ☒ 11 sheet(s) of ☐ formal ☒ informal drawing(s);
- ☐ a claim for foreign priority under 35 U.S.C. §§ 119 and/or 365 is ☐ hereby made to
filed in on ;
☐ in the declaration;
- ☐ a certified copy of the priority document;
- ☐ a Constructive Petition for Extensions of Time;
- ☐ _____ statement(s) claiming small entity status;
- ☒ an Assignment document;
- ☐ an Information Disclosure Statement; and
- ☐ Other: _____

The declaration of the inventor(s) [] also is enclosed [X] will follow.

- [] Please amend the specification by inserting before the first line the sentence --This application claims priority under 35 U.S.C. §§119 and/or 365 to __ filed in __ on __; the entire content of which is hereby incorporated by reference.--

The filing fee has been calculated as follows [] and in accordance with the enclosed preliminary amendment:

CLAIMS					
	NO. OF CLAIMS		EXTRA CLAIMS	RATE	FEE
Basic Application Fee					\$760.00
Total Claims	13	MINUS 20 =		x \$18.00	
Independent Claims	5	MINUS 3 =	2	x \$78.00	\$156.00
If multiple dependent claims are presented, add \$260.00					\$40.00
Total Application Fee					\$956.00
If verified Statement claiming small entity status is enclosed, subtract 50% of Total Application Fee					
Add Assignment Recording Fee of \$40.00 if Assignment document is enclosed					
TOTAL APPLICATION FEE DUE					\$956.00

[X] A check in the amount of \$ 956.00 is enclosed for the fee due.

[] Charge \$ _____ to Deposit Account No. 02-4800 for the fee due.

Please address all correspondence concerning the present application to:


Ronald L. Grudziecki
Burns, Doane, Swecker & Mathis, L.L.P.
P.O. Box 1404
Alexandria, Virginia 22313-1404.

The Commissioner is hereby authorized to charge any appropriate fees under 37 C.F.R. §§ 1.16, 1.17 and 1.21 that may be required by this paper, and to credit any overpayment, to Deposit Account No. 02-4800. This paper is submitted in triplicate.

Respectfully submitted,

BURNS, DOANE, SWECKER & MATHIS, L.L.P.

Date: January 26, 1999

By: 
John E. Harrity
Registration No. 43,367

P.O. Box 1404
Alexandria, Virginia 22313-1404
(703) 836-6620

**APPLICATION FOR
U.S. LETTERS PATENT**

BY

SANDEEP CHENNAKESHU

KAMBIZ ZANGI

and

GREGORY E. BOTTOMLEY

FOR

**REDUCED COMPLEXITY MLSE EQUALIZER
FOR M-ARY MODULATED SIGNALS**

BURNS, DOANE, SWECKER & MATHIS, L.L.P.
Post Office Box 1404
Alexandria, Virginia 22313-1404
(703) 836-6620

Attorney Docket No. 027575-174

REDUCED COMPLEXITY MLSE EQUALIZER FOR M-ARY MODULATED SIGNALS

BACKGROUND

5 Digital wireless communication systems are used to convey a variety of information between multiple locations. With digital communications, information is translated into a digital or binary form, referred to as bits, for communication purposes. The transmitter maps this bit stream into a modulated symbol stream, which is detected at the digital receiver and mapped back into bits and information.

10 In digital communications, the radio environment presents many difficulties that impede successful communications. One difficulty is that the signal level can fade because the signal may travel in multiple paths. As a result, signal images may arrive at the receiver antenna out of phase. This type of fading is commonly referred to as Rayleigh fading or fast fading. When the signal fades, the signal-to-noise ratio becomes lower, causing degradation in the quality of the communication link.

15 A second problem occurs when the multiple signal paths are much different in length. In this case, time dispersion occurs, in which multiple fading signal images arrive at the receiver antenna at different times, thus giving rise to signal echoes or rays. This causes intersymbol interference (ISI), where the echoes of one symbol interfere with subsequent symbols.

20 At the receiver, coherent demodulation is desirable, since it provides the best performance. This requires knowledge of the multipath channel. In many wireless applications, this channel is time-varying, due to transmitter motion, receiver motion, and/or scatterer motion. Thus, there is a need to track a time varying multipath channel.

25 To provide coherent demodulation of multipath signals, a maximum-likelihood-sequence-estimation (MLSE) equalizer may be employed. Such an equalizer considers

various hypotheses for the transmitted symbol sequence, and with a model of the dispersive channel, determines which hypothesis best fits the received data. This is efficiently realized using the Viterbi algorithm. This equalization technique is well known to those skilled in the art, and can be found in J.C. Proakis, Digital

5 Communications, 1989.

The conventional MLSE equalizer can be explained by a simple example. Suppose the transmitter transmits a symbol stream $s(n)$, which takes on values "+B" or "-B" corresponding to bit values 0 or 1, respectively. This stream is modulated using binary-shift keying (BPSK). At the receiver, the received signal is filtered, amplified,
10 and mixed down using the I and Q carriers, then sampled once every symbol period (T), giving a received signal stream $r(n)$. In this example, the intervening channel consists of two rays, a main ray and an echo, where the echo arrives T seconds later and T is the symbol period. Then the received signal can be modeled as

$$r(n) = c_0 s(n) + c_1 s(n - 1) + \eta(n), \quad (1)$$

15 where c_0 and c_1 are complex channel tap values and $\eta(n)$ is additive noise or interference.

In the MLSE equalizer, at iteration n , there would be two different previous "states," 0 and 1, corresponding to the two possible values for the previous symbols:

1. $s(n - 1) = B \leftrightarrow \text{Previous State} = 0$
- 20 2. $s(n - 1) = -B \leftrightarrow \text{Previous State} = 1.$

Associated with each previous state there would be an accumulated metric, accumulated from previous iterations, giving rise to accumulated metrics $A_0(n - 1)$ and $A_1(n - 1)$ for previous state 0 and previous state 1, respectively.

There would also be two current states corresponding to two possible values for
25 $s(n)$. Each possible pairing of a previous state with a current state corresponds to a

hypothetical sequence $\{s_h(n-1), s_h(n)\}$. For each of these hypotheses, there will be a corresponding hypothesized received signal value at time n :

$$r_h(n) = c_0 s_h(n) + c_1 s_h(n-1). \quad (2)$$

Furthermore, for each of these hypotheses, there will be a corresponding "branch"
5 metric given by

$$M_h(n) = |r(n) - r_h(n)|^2. \quad (3)$$

In the example, there are four possible hypothetical sequences which can be denoted by $h \in \{00, 01, 10, 11\}$, as illustrated in Table 1.

10

Previous State	Current State	h
0(B)	0(B)	00
1(-B)	0(B)	10
0(B)	1(-B)	01
1(-B)	1(-B)	11

15

Table 1: Naming Convention for States

20

The candidate metrics for each possible current state would be the sum of the corresponding branch metrics and the previously accumulated metric associated with $s_h(n-1)$. For each current state, there are two possible previous states. For each current state, the previous state which gives the smallest candidate metric is selected as the predecessor state, and the candidate metric becomes the accumulated metric for that current state.

Thus, for current state 0 (i.e., $s(n)=B$), there will be two hypothetical sequences $\{s_h(n-1) = B, s_h(n) = B\}$ or $\{s_h(n-1) = -B, s_h(n) = B\}$, denoted by hypotheses $h = 00$ and $h = 10$. This gives rise to two candidate metrics for current state 0:

$$5 \quad C_{00}(n) = A_0(n-1) + M_{00}(n) \quad (4)$$

$$C_{10}(n) = A_1(n-1) + M_{10}(n). \quad (5)$$

The smaller of these two candidate metrics gives the accumulated metric for current state 0. The corresponding previous state becomes the predecessor state to state 0 at time n :

- 10 1. If $C_{10}(n) < C_{00}(n)$, $A_0(n) = C_{10}(n)$
2. If $C_{00}(n) < C_{10}(n)$, $A_0(n) = C_{00}(n)$

A similar procedure is applied to current state 1 (i.e., $s(n) = -B$), in which case the two hypotheses are $h = 01$ and $h = 11$.

For each n , four hypothesized received signal values must be computed according to equation (2). Computing each hypothesized value $r_h(n)$ involves two multiplication operations. Each of these multiplication operations involves the product of one of the channel taps and a hypothetical symbol value.

If B is set to $+1$, the multiplications become simply sign changes. However, if amplitude modulation is used, this is not possible. Also, suppose symbol values can be normalized to $\left\{ e^{j\frac{2\pi\ell}{8}} \right\}_{\ell=0}^7$ (i.e., 8PSK modulation). In this case, the necessary multiplications can not be implemented as simple sign changes.

One way to increase the throughput over a digital channel is to allow each transmitted symbol to take on more than two values. In general, each symbol might be chosen from a set of M possible values $\{B_1, B_2, \dots, B_M\}$ thereby increasing the number of bits per symbol. The complexity of the conventional implementation of the MLSE

equalizer increases exponentially with the number of allowed symbols (i.e., with M). Specifically, with " L " channel taps, the number of multiplications needed for the conventional implementation of the equalizer is proportional (proportionality constant greater than one) to M^{L-1} .

5 Even with moderate values for M and L (e.g., 8 and 5 respectively), it is impractical to implement the equalizer in grand purpose DSPs with low power consumption. The trend in power sensitive applications is to move away from DSPs toward ASICs. ASICs can be optimized for performing one task with low power consumption and small size (i.e., small gate count). Implementing multipliers in an
10 ASIC is much more expensive (in terms of power consumption and gate count) than implementing circuits for addition or subtraction. Therefore, it is highly desirable to avoid many of the multiplications associated with the conventional implementation of MLSE equalizers.

 Because of the trend toward increasing the number of required multiplication
15 operations and due to the fact that technology is moving away from DSPs, where multiplication operations are easy, toward ASICs, where multiplications are relatively expensive, it is desirable to reduce the number of multiplications actually performed by the MLSE.

SUMMARY

20 This disclosure concerns demodulation of radio signals modulated with M -ary modulation in the presence of intersymbol interference distortion. The invention presents a method for reducing the number of multiplications needed to implement an MLSE equalizer for signals modulated with M -ary modulation.

 In exemplary embodiments of the present invention, the number of
25 multiplications is reduced by pre-computing certain values needed for the determination of the branch metric and storing these pre-computed values in a product table. When a branch metric computation is to be made, whether it is an Euclidean branch metric

computation or an Ungerboeck branch metric computation, certain multiplication operations are replaced by simple table look-up operations. As a result, the power consumption and size of the equalizer are reduced.

Any receiver that demodulates signals that are modulated with M-ary modulation can be implemented using the instant invention. The resulting demodulator will have a lower complexity than existing demodulators.

BRIEF DESCRIPTION OF THE DRAWINGS

The above objects and features of the present invention will be more apparent from the following description of the preferred embodiments with reference to the accompanying drawings, wherein:

Figure 1 illustrates a radio communication system within which the techniques according to the present invention can be implemented;

Figure 2 illustrates a functional block diagram of the baseband processor of Figure 1;

Figure 3 illustrates a functional block diagram of the transmission function of Figure 1;

Figure 4 illustrates a system for computing an Euclidean branch metric within which the techniques according to the instant invention may be implemented;

Figure 5 illustrates a functional block diagram of a filter used to compute an Euclidean metric according to the prior art;

Figure 6 illustrates a product table for the Euclidean metric according to one embodiment of the present invention;

Figure 7 illustrates a functional block diagram of the filter for computing the Euclidean metric according to one embodiment of the present invention;

Figure 8 illustrates a system for computing an Ungerboeck branch metric within which the techniques according to the instant invention may be implemented;

Figure 9 illustrates a functional block diagram of a conventional filter used to compute the Ungerboeck metric according to the prior art;

Figure 10 illustrates a product table for the Ungerboeck metric according to one embodiment of the present invention; and

5 Figure 11 illustrates a functional block diagram of the filter for computing the Ungerboeck metric according to one embodiment of the present invention.

DETAILED DESCRIPTION

Figure 1 illustrates a radio communication system within which the present invention may be implemented. In Figure 1, a radio transmitter and receiver for a
10 radio communication system are provided. The radio communication system may operate using FDMA, TDMA, or CDMA, or some combination thereof. A transmitter has a digital symbol generator 102 which receives an information carrying signal 101 and generates a corresponding digital symbol sequence, S . The symbols S are subjected to digital-to-analog (D/A) conversion, modulation, pulse shape filtering and
15 amplification, and are transmitted as analog signal Y by digital transmitter 103 according to known techniques.

Signal Y travels through the radio channel and is intercepted by the antenna 104 at the receiver. Thermal noise n is also intercepted by the antenna 104.

Radio unit 105 amplifies, down-converts, and filters the received signal
20 according to known methods to produce an analog output. This analog output is coupled to an A/D converter 106 which converts the analog signal into a received signal sample stream $r(kT_s)$, where T_s is the sample period, and k is an integer counter. The sampling period T_s may be less than the symbol period T . The received signal sample streams are collected in processor 107, which processes this stream to produce
25 an estimate of the transmitted digital symbol stream \hat{S} . In later descriptions, transmission function 109 is used to refer to the signal path through digital transmitter 103, the radio transmission channel 105, and A/D 106 collectively.

The transmission function 109 produces the received signal sample stream $r(kT_s)$ which is sent to processing unit 107 where it is processed in accordance with the present invention.

A functional block diagram of the baseband processing unit 107 is illustrated in Figure 2. The received signal sample stream $r(kT_s)$ is coupled to a signal pre-processor, or sync, 206 where the received signal sample stream is correlated with a known timing/synchronization sequence according to known techniques. For the case of symbol-spaced demodulation, if the sample period T_s is less than the symbol period T , the signal pre-processor 206 performs a decimation of the received signal sample stream $r(kT_s)$ to produce one sample per symbol, designated as $r(n)$. For fractionally-spaced demodulation, more than one sample per symbol is generated.

Estimating circuit 202 produces channel tap estimates $c(\tau)$ which are used to model the radio transmission channel according to known techniques. This might involve an initial channel estimation period followed by a tracking period. The channel tap estimates $c(\tau)$ are coupled to the input of the branch metric processor 203. The branch metric processor 203 is coupled to a sequence estimation processor 204 which provides an estimate of the digital symbol stream \hat{S} .

The transmission function 109 is illustrated in more detail in Figure 3, where for simplicity, the number of received antennas is restricted to one. One skilled in the art will appreciate that the present invention may also be used for the case where there are two or more antennas. In Figure 3, the symbol sequence S is input to the digital transmitter 103 which transmits analog signal Y . The analog signal Y propagates through a radio transmission channel to the radio unit 105. Radio channel 301 may introduce fading and time dispersion. Omnipresent thermal noise n is also received. Radio unit 105 amplifies, down-converts, and filters the received signal according to known techniques to produce an analog signal. This analog signal is coupled to an A/D 106 which converts this analog signal into the received signal samples $r(kT_s)$.

In an MLSE equalizer, all possible transmitted symbol sequences S are effectively considered. In one implementation, hypothesized symbol values $s_h(n)$ are filtered by channel tap estimates $c(\tau)$ to produce hypothesized received samples $r_h(n)$. The difference between the hypothesized $r_h(n)$ and the actual $r(n)$ received signal sample stream, referred to as the hypothesis error $e(n)$, gives an indication of how good a particular hypothesis is. The squared magnitude of the hypothesis error is used as a metric to evaluate a particular hypothesis. The metric is accumulated for different hypotheses for use in determining which hypotheses are better using the sequence estimation algorithm. This process may be efficiently realized using the Viterbi algorithm. A description of the Viterbi algorithm can be found in G. Forney, Jr., "The Viterbi Algorithm," Proceedings of the IEEE, vol. 61, no. 3, March 1973, pp. 267-278. As will be appreciated by one skilled in the art, other sequence estimation algorithms may also be used.

In an MLSE equalizer, there are states associated with different transmitted sequence hypotheses $s_h(n)$. At a given iteration, there are previous states, each of which is associated with an accumulated metric. Each pairing of a previous state with a current state results in a branch metric $M_h(n)$. The candidate metric for a current state is then the sum of this branch metric $M_h(n)$ and the previously accumulated metric. For each current state, the previous state which gives the smallest candidate metric is selected as the predecessor state, and the smallest candidate metric becomes the accumulated metric for the current state. The branch metric can be expressed as:

$$M_h(n) = |r(n) - r_h(n)|^2 \quad (6)$$

where

$$r_h(n) = \sum_{k=0}^{N_t-1} c(k)s_h(n - k). \quad (7)$$

The channel tap estimates are designated by $c(\tau)$ where τ is the delay (i.e. $\tau = 0$ is the main ray, $\tau = 1$ is the first echo, etc). N_t is the number of channel taps estimated. For each n , the hypothesized received signal $r_h(n)$ must be computed according to equation (7). In the most general case, computing each hypothesized received value $r_h(n)$ involves N_t complex multiplications (i.e. $4N_t$ real multiplications). Each of these complex-valued multiplications involves the product of one of the estimated channel taps and a hypothesized transmitted signal.

Figure 4 illustrates a system for computing an Euclidean branch metric $M_h(n)$ within which the techniques according to the instant invention may be implemented. In Figure 4, the hypothesized sequence of symbols $s_h(n)$ which is generated by symbol sequence generator 410 is coupled into filter 400 to produce the hypothesized received samples $r_h(n)$. The difference between the hypothesized received samples $r_h(n)$ and the actual received signal sample stream $r(n)$ is the hypothesized error $e(n)$. The squared magnitude of the hypothesized error is performed by unit 403 to produce the branch metric $M_h(n)$.

A functional block diagram of a conventional filter for computing an Euclidean branch metric is illustrated in Figure 5. In Figure 5, N_t complex multiplications are performed to compute each $r_h(n)$. If the transmitted symbols are restricted to be in a set of M possible values, $\{B_1, B_2, \dots, B_M\}$, the present invention provides a method for implementing the filter 400 that avoids performing any multiplications.

With an Euclidean metric, assume that each hypothesized transmitted symbol $s_h(n)$ is in the set $\{B_1, B_2, \dots, B_M\}$. The first term in the sum in equation (7) is in the set $\{B_i c(0)\}_{i=1}^M$. All the members of this set can be pre-computed and stored in the first column of an $M \times N_t$ table (see Figure 6).

The j -th column of this table, corresponding to estimated channel tap $c(j - 1)$, stores all the possible values of $(s_h(.)c(j - 1))$, i.e. $\{B_1 c(j - 1), B_2 c(j - 1), \dots, B_M c(j - 1)\}$. Each hypothesized received value $r_h(n)$ can then be computed by simply adding the appropriate entries from this product table (see Figure 7).

As a concrete example, consider a two-tap channel (c_0, c_1) with 8PSK modulation i.e., $s_h(n) \in \left\{ e^{j\frac{2\pi}{8}\ell} \right\}_{\ell=0}^7$. In this case, the first column of the table illustrated in Figure 6 will have 8 entries, corresponding to channel tap c_0 , as:

$$\left[e^{j\frac{2\pi}{8}0} c_0, e^{j\frac{2\pi}{8}1} c_0, e^{j\frac{2\pi}{8}2} c_0, \dots, e^{j\frac{2\pi}{8}7} c_0 \right]. \quad (8)$$

Similarly, the second column of the table in Figure 6 will have 8 entries, corresponding to channel tap c_1 , as:

$$\left[e^{j\frac{2\pi}{8}0} c_1, e^{j\frac{2\pi}{8}1} c_1, e^{j\frac{2\pi}{8}2} c_1, \dots, e^{j\frac{2\pi}{8}7} c_1 \right]. \quad (9)$$

Symmetry can be used to reduce storage requirements. First, negative symmetry can be used to halve the items stored. Basically,

$$e^{j\frac{2\pi}{8}\ell + \pi} c_0 = - e^{j\frac{2\pi}{8}\ell} c_0. \quad (10)$$

Therefore, only values for $\ell = 0, 1, 2, 3$ need to be stored. Furthermore,

$$e^{j\frac{2\pi}{8}2} c_0 = j e^{j\frac{2\pi}{8}0} c_0 \quad (11)$$

and

$$e^{j\frac{2\pi}{8}3} c_0 = j e^{j\frac{2\pi}{8}(1)} c_0. \quad (12)$$

Thus, by switching real and imaginary parts and negating the new real part, one only needs to store values for $\ell = 0$ and 1. For $\ell = 0$, no multiplication is necessary since

$$e^{j\frac{2\pi}{8}0} c_0 = c_0. \quad (13)$$

Thus, one can simply store c_0 and $e^{j\pi/4}c_0$ and derive the other values using logic that negates and possibly switches real and imaginary parts. This savings results from the quadrantile symmetry in the 8PSK signal constellation.

5 The Ungerboeck metric is obtained from the Euclidean metric $M_h(n)$ of equation (3) in two steps. The first step is to expand $M_h(n)$ to get

$$M_h(n) = A(n) + B(n) + C(n) + D(n), \quad (14)$$

where

$$A(n) = |r(n)|^2 \quad (15)$$

$$B(n) = -2\text{Re}\{r(n)c_0^* s_h^*(n)\} - 2\text{Re}\{r(n)c_1^* s_h^*(n-1)\} \quad (16)$$

$$C(n) = |c_0|^2 |s_h(n)|^2 + |c_1|^2 |s_h(n-1)|^2 \quad (17)$$

$$D(n) = 2\text{Re}\{c_0 c_1^* s_h(n) s_h^*(n-1)\}. \quad (18)$$

10 The Ungerboeck method drops the term $A(n)$, which is common to all hypotheses. The second step combines terms proportional to $s_h^*(n)$ from different iterations. At iteration $(n + 1)$, the terms become:

$$B(n+1) = -2\text{Re}\{r(n+1)c_0^* s_h^*(n+1)\} - 2\text{Re}\{r(n+1)c_1^* s_h^*(n)\} \quad (19)$$

$$C(n+1) = |c_0|^2 |s_h(n+1)|^2 + |c_1|^2 |s_h(n)|^2 \quad (20)$$

15 $D(n+1) = 2\text{Re}\{c_0 c_1^* s_h(n+1) s_h^*(n)\}. \quad (21)$

Thus, there are terms proportional to $s_h^*(n)$ in both iterations. These terms can be combined by defining a new metric, $M'_h(n)$, as

$$M'_h(n) = \text{Re} \{s_h^*(n) [-2z(n) + q_0 s_h(n) + q_1 s_h(n-1)]\} \quad (22)$$

where

$$z(n) = c_0^* r(n) + c_1^* r(n+1) \quad (23)$$

$$q_0 = |c_0|^2 + |c_1|^2 \quad (24)$$

$$q_1 = 2c_0 c_1^* \quad (25)$$

Here, q_0 and q_1 are referred to as s-parameters.

Thus with an Ungerboeck metric, the branch metric $M'_h(n)$ is defined as:

$$M'_h(n) = \text{Re} \{s_h^*(n) [-2z(n) + t_h(n)]\}, \quad (26)$$

10 where

$$t_h(n) = \sum_{k=0}^{N_t-1} q(k) s_h(n-k). \quad (27)$$

Figure 8 illustrates a system for computing an Ungerboeck branch metric within which the techniques according to the instant invention may be implemented. In Figure 8, the hypothesized symbols $s_h(n)$ are coupled into the filter 600, with impulse response $q(\tau)$, to produce the $t_h(n)$. $q(\tau)$'s are determined from the estimated channel taps $c(\tau)$'s; hence, $q(\tau)$'s do not depend on the hypothesized symbols $s_h(n)$. The current state of the art for implementing a filter of Figure 8 requires N_t complex multiplications, as illustrated in Figure 9.

Assume that each hypothesized transmitted symbol $s_h(n)$ is in the set $\{B_1, B_2, \dots, B_M\}$. The first term in the sum in equation (27) is in the set $\{B_i q(0)\}_{i=1}^M$. All the members of this set can be pre-computed and stored in the first column of an $M \times N_t$ table (see Figure 10).

- 5 The j -th column of this table, corresponding to $q(j-1)$, stores all the possible values of $s_h(.)q(j-1)$, i.e., $\{B_1 q(j-1), B_2 q(j-1), \dots, B_M q(j-1)\}$. Each hypothesized $t_h(n)$ can then be computed by simply adding the appropriate entries from this product table (see Figure 11).

- 10 As described earlier, quadrant symmetry can be used to reduce the number of items stored in each column to two.

- The partial Ungerboeck metric also has terms like q_i set forth in the previous section; hence, the present invention can be used to reduce the number of multiplications needed to implement a demodulator that uses the partial Ungerboeck metric. The partial Ungerboeck metric is disclosed in U.S. Patent 5,499,272 to
15 Bottomley.

For a multi-channel MLSE with Euclidean metric, the transmitted symbol stream is received via several channels. With two channels, there would be two received signals $r_a(n)$ and $r_b(n)$, corresponding to channels a and b respectively:

$$r_a(n) = c_{a0}s(n) + c_{a1}s(n-1) + \eta_a(n) \quad (28)$$

20 $r_b(n) = c_{b0}s(n) + c_{b1}s(n-1) + \eta_b(n). \quad (29)$

Corresponding to each received signal and each hypothesized symbol sequence, there would be a branch error signal:

$$e_{ah}(n) = r_a(n) - r_{ah}(n) \quad (30)$$

$$e_{bh}(n) = r_b(n) - r_{bh}(n), \quad (31)$$

- 25 where $r_{ah}(n)$ and $r_{bh}(n)$ are the hypothesized received signals for channel a and channel b (both corresponding to the same hypothesized sequence $\{s_h(n-1), s_h(n-1)\}$):

$$r_{ah}(n) = c_{a0}s_h(n) + c_{a1}s_h(n-1) \quad (32)$$

$$r_{bh}(n) = c_{b0}s_h(n) + c_{b1}s_h(n-1). \quad (33)$$

Note that one branch metric for channel a is $e_{ah}(n)e_{ah}^*(n)$, and one branch metric for channel b is $e_{bh}(n)e_{bh}^*(n)$.

Different branch metrics for the joint equalization of the outputs of both channels can be obtained by combining $e_{ah}(n)$ and $e_{bh}(n)$ in different ways. Several
 5 interesting branch metrics for the joint equalization problem can be expressed in the following form:

$$M_h(n) = E_h(n)^H Q E_h(n), \quad (34)$$

where

$$E_h(n) = \begin{bmatrix} e_{ah}(n) \\ e_{bh}(n) \end{bmatrix} \quad (35)$$

and Q is a two by two weighting matrix.

10 Any branch metric of the form given by equation (34) can be computed efficiently using two pre-computed tables. Each hypothesized received signal $r_{ah}(n)$ or $r_{bh}(n)$ can be computed without performing a multiplication operation by using two pre-computed tables.

It would be appreciated by one skilled in the art how the present invention can
 15 be used when more than two channels are received. Similarly, it would be appreciated by one skilled in the art how the present invention can be used when the symbols can take on one of M possible values.

In metric combining, the weighting matrix Q is a diagonal matrix. The diagonal entries of this matrix are the weighting coefficients for each channel.

20 In Interference Rejection Combining (IRC), the weighting matrix Q is the inverse of the correlation matrix of the impairment. Specifically, the impairment vector $i(n)$ may be defined as

$$i(n) = \begin{bmatrix} \eta_a(n) \\ \eta_b(n) \end{bmatrix}, \quad (36)$$

and let $R_{\eta\eta} = E\{i(n)i(n)^H\}$. In IRC, the weighting matrix Q is simply $Q = R_{\eta\eta}^{-1}$. IRC is described more fully in U.S. Patent No. 5,680,419 which is incorporated by reference herein.

For a multi-channel MLSE with Ungerboeck metric, consider the case with two channels; hence, for each "n" there would be two received samples $r_a(n)$ and $r_b(n)$ as given by equations (28)-(29).

In this case, the Ungerboeck branch metric is given by:

$$M'_h(n) = \text{Re}\{s_h^*(n)[-2z(n) + q_0 s_h(n) + q_1 s_h(n-1)]\} \quad (37)$$

where $z(n)$ is obtained from both received signals and both channel taps, and (q_0, q_1) are obtained from both channel taps and the inverse of the impairment's correlation matrix (see US Patent 5,680,419). It is important to note that (q_0, q_1) do not depend on the hypothesized symbols and are fixed.

From equation (37), it is evident that computing $M'_h(n)$ in the multi-channel case requires computing

$$t_h(n) = q_0 s_h(n) + q_1 s_h(n-1). \quad (38)$$

Computing $t_h(n)$ would normally require two multiplications. These multiplications can be avoided by pre-computing the values $\{sq_0, sq_1\}$ for possible symbol values s and

storing them in a table in memory. Any hypothetical t_h can then be computed by adding the appropriate entries from this pre-computed table.

It would be appreciated by one skilled in the art how the present invention can be used when more than two channels are received. Similarly, it would be appreciated
5 by one skilled in the art how the present invention can be used when the symbols can take on one of M possible values.

For the case of fractionally-spaced MLSE equalization, a $(T/2)$ fractionally-spaced MLSE equalizer will receive two samples in each sampling interval of length T . Let $r_a(n)$ represent the even samples of the received signal, and let $r_b(n)$ represent the
10 odd samples of the received signal. Note the $r_a(n)$ and $r_b(n)$ are symbol-spaced. In a particular implementation of the fractionally-spaced MLSE equalizer, $r_a(n)$ and $r_b(n)$ are treated as two separate received signals (resulting from the same transmitted symbol stream). According to this exemplary embodiment, the two-input MLSE equalizer of the last section is used to detect the transmitted symbol stream. The techniques
15 disclosed above for reducing the complexity of the diversity of the MLSE equalizer are obviously applicable to this implementation of the fractionally-spaced MLSE equalizer.

It would be appreciated by one skilled in the art how the present invention can be used with other forms of fractionally-spaced equalization. For example, in one particular realization of the fractionally-spaced equalizer, a pre-whitening filter is
20 applied to each sub-sampled sequence (see Hamied and Stuber, "A Fractionally Spaced MLSE Receiver," IEEE 1995). This particular formulation is very similar to metric combining. In yet another formulation of the fractionally-spaced equalizer, an Ungerboeck metric is used; hence, the present invention can again be used to reduce the complexity of this equalizer. It would also be appreciated by one skilled in the art
25 how the present invention can be used when more than two samples are received per symbol.

For a MLSE with a time-varying channel, at each iteration, a different set of channel taps might be considered. With the Euclidean metric, the hypothesized received signal is expressed as:

$$r_h(n) = c_0(n) s_h(n) + c_1(n) s_h(n-1) \quad (39)$$

5 In this case, at iteration "n", the table might be updated and used for computing all the different hypothesized received values at this iteration. A new table is computed for iteration "n + 1" and so forth.

10 It would be appreciated by one skilled in the art how the present invention can be used when the Ungerboeck metric is used with a time-varying channel. The table would be updated every time the q_i 's are updated.

For demodulation of signals modulated using offset M-ary modulation, the present invention can be modified to reduce the complexity of the demodulator even further. In offset M-ary modulation, the transmitted symbols for even "n" are purely real, and the transmitted symbols for odd "n" are purely imaginary:

$$15 \quad s(n) = j^n B_i \quad i \in \{1, \dots, M\}, \quad (40)$$

where each B_i is purely real. Hence, $s_h(n)$ can take one of $2M$ values $\{B_i, jB_i\}_{i=1}^M$.

20 However, by pre-rotating the received signal $r(n)$ by j^{-n} we can reduce the demodulation problem to demodulating purely real symbols where each real symbol is in the set $\{B_i\}_{i=1}^M$. With this pre-rotation, we would only need to store the product of the channels taps and each of $\{B_i\}_{i=1}^M$'s.

It will be apparent to one of ordinary skill in the art that the present invention may be practiced in other embodiments that depart from these specific details. In other instances, detailed description of well-known methods, devices, and circuits are omitted so as not to obscure the description of the present invention with unnecessary details.

Many variants and combinations of the techniques taught above may be devised by a person skilled in the art without departing from the spirit or scope of the invention as described by the following claims.

Continued on next page

WHAT IS CLAIMED IS:

1. A method for determining a branch metric in a maximum-likelihood-sequence-estimation equalizer which receives at least one antenna signal modulated with M-ary modulation, said method comprising the steps of:

- 5 pre-computing values equal to a product of a complex number and a hypothetical symbol value;
 storing said pre-computed values in a product table;
 adding select pre-computed values from said product table to produce a result; and
10 determining said branch metric using said result.

2. The method of claim 1 wherein said complex number corresponds to a channel coefficient.

3. The method of claim 1 wherein said complex number corresponds to a s-parameter.

- 15 4. A filter in a maximum-likelihood-sequence-estimation equalizer, which demodulates at least one received radio signal modulated with M-ary modulation, for producing a hypothesized received signal sample to be used for determining a branch metric, said filter comprising:

 a memory for storing a product table having pre-computed values equal
20 to a product of a channel tap estimate and a hypothetical symbol value for different iterations; and
 an adder for adding select entries from the product table to produce a hypothesized received signal sample.

5. A filter in a maximum-likelihood-sequence-estimation equalizer for M-ary modulation, said filter comprising:

means for pre-computing a plurality of possible values to be used in determining a branch metric;

5 a memory for storing said plurality of pre-computed possible values; and
means for combining select pre-computed values from said memory.

6. The filter according to claim 5 wherein said branch metric is an Ungerboeck branch metric.

7. The filter according to claim 5 wherein said branch metric is an
10 Euclidean branch metric.

8. The filter according to claim 5 wherein said branch metric is a partial Ungerboeck branch metric.

9. A method for computing a branch metric in maximum-likelihood-sequence-estimation equalizer which demodulates M-ary modulated signals, said
15 method comprising the steps of:

pre-computing a plurality of possible values to be used in the branch metric computation;

storing said plurality of pre-computed possible values in a memory;
adding select pre-computed values from said memory; and
20 computing said branch metric using said added select pre-computed values.

10. The method according to claim 9 wherein said branch metric is an Ungerboeck branch metric.

11. The method according to claim 9 wherein said branch metric is a partial Ungerboeck branch metric.

12. The method according to claim 9 wherein said branch metric is an Euclidean branch metric.

5 13. A method for computing a branch metric in a multi-channel maximum-likelihood-sequence-estimation (MLSE) equalizer which demodulates M-ary modulated signals, said method comprising the steps of:

pre-computing a plurality of possible values for each channel in said multi-channel MLSE to be used in the branch metric computation;

10 storing said plurality of possible values for each channel in separate product tables;

adding select values from said separate product tables; and

computing said branch metric using said added select values.

027575-174

THE **NEW** **YORK** **PUBLIC** **LIBRARY** **ASTOR LENOX TILDEN FOUNDATION**

THE **NEW** **YORK** **PUBLIC** **LIBRARY** **ASTOR LENOX TILDEN FOUNDATION**




Figure 1




Figure 2




Figure 3




Figure 4

$c(n)$ S_h						
	$c(0)B(1)$	$c(1)B(1)$	•	•	•	$c(Nt-1)B(1)$
	$c(0)B(2)$	$c(1)B(2)$	•	•	•	$c(Nt-1)B(2)$
				•		
				•		
				•		
	$c(0)B(M)$	$c(1)B(M)$	•	•	•	$c(Nt-1)B(M)$

500

Figure 6




Figure 7




Figure 8




Figure 9. (PRIOR ART)

S_h $c(n)$

$q(0)B(1)$	$q(1)B(1)$	•	•	•	$q(Nt-1)B(1)$
$q(0)B(2)$	$q(1)B(2)$	•	•	•	$q(Nt-1)B(2)$
			•		
			•		
			•		
$q(0)B(M)$	$q(1)B(M)$	•	•	•	$q(Nt-1)B(M)$

550

Figure 10

659270 "9522250




Figure 11